

WS-1 WATER LEAKAGE DETECTOR



This product is perfect for detecting different types of water leakage:

- flood;
- heating system malfunction;
- ventilation system malfunction;
- air conditioning system malfunction;
- plumbing system malfunction;
- other.

WS-1 is a water sensor that works on 12vdc alarm panels on a 24-hr. zone, open loop circuit. The wiring works similar to a two-wire smoke detector. The sensor draws a low current from the alarm panel's 24-hour open loop circuit. When the terminals on the bottom of the sensor get wet from the water, the transistor inside locks down to close the circuit, causing the panel to send an alarm signal.

SPECIFICATIONS	
Supply Voltage	12V DC (9V min)
Current Consumption	10 mA
Dimensions (WxHxD)	12x12x63 mm
Connecting wires	170cm
Mounting Method	Screwed